

DIGIEVER Network Camera Compatibility List

The list is applied for DIGIEVER NVR firmware 78-2 version or later

Update: Oct. 2024

● DIGIEVER NVR supports the camera feat * Camera does not support the feature Blank means the feature is NOT supported or verified by DIGIEVER

Ⓟ 360° Panoramic Ⓞ NVR support camera hardware dewarp setting

Ⓢ NVR support camera software dewarp

◆ Camera takes more than 1CH, needed to be added via video sever method

- | | | | |
|----------------|------------------------------|-----------------------------|------------------------------------|
| IVA Event No.: | 1. Audio Detection | 5. Intrusion Detection | 9. People Counting Threshold Alarm |
| | 2. Advanced Motion Detection | 6. Loitering Detection | 10. Temperature Detection |
| | 3. Human Detection | 7. Foreign Object Detection | 11. Camera Tampering Detection |
| | 4. Cross Line Detection | 8. Missing Object Detection | 12. Object Status Change |

Supported in the NVR latest version

Copyright © DIGIEVER Corporation All Rights Reserved * Please contact DIGIEVER sales for updated information

Brand	Camera Model	Compression Format				Zoom Control			Basic Function					Advanced Function			Remark	Not support in other platforms CMS, VD, SS	
		MJPEG	MPEG-4	H.264	H.265	Pan/Tilt	Optical Zoom	Digital Zoom	Motion Detection	Digital Input	Audio (Besides HTTP)	Two-way Audio	Edge Record (RTSP)	Supported IVA	AI Search (Metadata)	Advanced Right-Click Menu			Camera Firmware/ Note
AXIS	AXIS cameras																		
	AXIS 211W	●	●	*	*	*	*	●	●		●	*		1				4.44.1	
	AXIS 212 PTZ	●	●	*	*	●	*	●	●		●	*		1					
	AXIS 212 PTZ-V	●	●	*	*	●	*	*	●		*	*							
	AXIS 214 PTZ	●	●	*	*	●	●	●	●		●	*		1					
	AXIS 215 PTZ	●	●	*	*	●	●	●	●		●	*		1				4.49	
	AXIS 215 PTZ-E	●	●	*	*	●	●	●	●		*	*							
	AXIS 216FD	●	●	*	*	●	*	●	●		●	*		1					
	AXIS 216FD-V	●	●	*	*	●	*	●	●		●	*		1					
	AXIS 216MFD	●	●	*	*	●		●	●		●	*		1					
	AXIS 216MFD	●	●	*	*	●	*	●	●		●	*		1					
	AXIS 221	●	●	*	*	*	*	●	●		*	*							
	AXIS 225FD	●	●	*	*	*	*	●	●		*	*							
	AXIS 232D	●	●	*	*	●	●	●	●		*	*							
	AXIS 233D	●	●	*	*	●	●	●	●		●	*		1				4.48.4	
	AXIS A8004-VE	●	*	●	*	*	*	●	●		●	*		1				5.65.1	
	AXIS FA51	●	*	●	*	*	*	●	● (TCP)	●	*	*	●					10.12.182	
	AXIS FA54 Main Unit	●	*	●	*	*	*	●	●	●	●	●	●	1				10.11.65 * Each channel support 1 camera D/I (total 4-ch)	
	AXIS M1004-W	●	*	●	*	*	*	●	●		●	*		1					
	AXIS M1011	●	●	●	*	*	*	●	●	*	*	*							
	AXIS M1011-W	●	●	●	*	*	*	●	●	*	*	*							
	AXIS M1013	●	●	●	*	*	*	●	●	*	*	*							
	AXIS M1014	●	●	●	*	*	*	●	●	*	*	*							
	AXIS M1025	●	*	●	*	*	*	●	●	*	*	*							
	AXIS M1031-W	●	●	●	*	*	*	●	●	*	●	*		1					
	AXIS M1033-W	●	*	●	*	*	*	●	●	*	●	*		1					
	AXIS M1034-W	●	*	●	*	*	*	●	●		●	*		1					
	AXIS M1045-LW	●	*	●	*	*	*	●	●	*	*	*							
	AXIS M1054	●	*	●	*	*	*	●	●		●	*		1					
	AXIS M1055-L	●	*	●	●	*	*	●	● (TCP)	●	*	*	●					11.5.64	
	AXIS M1065	●	*	●	*	*	*	●	●	*	●	*		1				6.15.4	
	AXIS M1065L	●	*	●	*	*	*	●	●	*	●	*		1				6.15.4	
	AXIS M1065-L	●	*	●	*	*	*	●	●	*	●	*		1					
	AXIS M1065LW	●	*	●	*	*	*	●	●	*	●	*		1				6.15.4	
	AXIS M1065-LW	●	*	●	*	*	*	●	●	*	●	*		1					
	AXIS M1075-L	●	*	●	●	*	*	●	● (TCP)	●	●	●	●	1				11.2.53	
	AXIS M1103	●	*	●	*	*	*	●	●		*	*						5.09.1	
	AXIS M1104	●	*	●	*	*	*	●	●		*	*							
	AXIS M1113	●	*	●	*	*	*	●	●		*	*							

Brand	Camera Model	Compression Format				Zoom Control			Basic Function				Advanced Function				Remark	
		MJPEG	MPEG-4	H.264	H.265	Pan/Tilt	Optical Zoom	Digital Zoom	Motion Detection	Digital Input	Audio (Besides HTTP)	Two-way Audio	Edge Record (RTSP)	Supported IVA	AI Search (Metadata)	Advanced Right-Click Menu	Camera Firmware/ Note	Not support in other platforms CMS, VD, SS
	AXIS M1113-E	●	*	●	*	*	*	●	●	*	*							
	AXIS M1114	●	*	●	*	*	*	●	●	*	*							
	AXIS M1114-E	●	*	●	*	*	*	●	●	●	*		1					
	AXIS M1124	●	*	●	*	*	*	●	●	*	*					6.35.2		
	AXIS M1124-E	●	*	●	*	*	*	●	●	*	*					6.35.2		
	AXIS M1125	●	*	●	*	*	*	●	●	●	*		1			8.15.1		
	AXIS M1125-E	●	*	●	*	*	*	●	●	*	*					5.75.3		
	AXIS M1134	●	*	●	●	*	*	●	●	●	*		1			9.50.1		
	AXIS M1135	●	*	●	●	*	*	●	● (TCP)	●	●	*	1			10.0.2		
	AXIS M1135 MkII	●	*	●	*	*	*	●	● (TCP)	●	●	●	1			10.12.182		
	AXIS M1137-E Mk II	●	*	●	●	*	*	●	● (TCP)	●	●	●	1, 12			10.12.127		
	AXIS M1143-L	●	*	●	*	*	*	●	●	*	*							
	AXIS M1144-L	●	*	●	*	*	*	●	●	*	*							
	AXIS M1145	●	*	●	*	*	*	●	●	*	*					5.90.1		
	AXIS M1145-L	●	*	●	*	*	*	●	●	*	*					5.90.1		
	AXIS M2014-E	●	*	●	*	*	*	●	●	*	*							
	AXIS M2025-LE	●	*	●	*	*	*	●	● (TCP)	*	*	*				9.80.1.2		
	AXIS M2026-LE	●	*	●	*	*	*	●	●	*	*	*				*Support motion detection TCP mode after camera FW(8.0.0)		
	AXIS M2026-LE Mk II	●	*	●	●	*	*	●	●	*	*	*				7.30.1.1		
	AXIS M2035	●	*	●	●	*	*	●	●	*	*	*				10.10.62		
	AXIS M2035-LE	●	*	●	●	*	*	●	●	*	*	*				10.10.62		
	AXIS M2036-LE	●	*	●	●	*	*	●	● (TCP)	*	*	*				10.11.65		
	AXIS M3004-V	●	*	●	*	*	*	●	●	*	*							
	AXIS M3005-V	●	*	●	*	*	*	●	●	*	*							
	AXIS M3006-P	●	*	●	*	*	*	●	●	*	*					5.40.5.7		
	AXIS M3006-V	●	*	●	*	*	*	●	●	*	*					5.40.5.7		
	AXIS M3007 (P,C)	●	*	●	*	*	*	●	●	*	*					5.70.1		
	AXIS M3007-P (P,C,S)	●	*	●	*	*	*	●	●	*	*					5.70.1		
	AXIS M3007-PV (P,C,S)	●	*	●	*	*	*	●	●	*	*					5.70.1		
	AXIS M3011	●	*	●	*	*	*	●	●	*	*							
	AXIS M3014	●	*	●	*	*	*	●	●	*	*							
	AXIS M3015	●	*	●	●	*	*	●	●	*	*					9.80.2		
	AXIS M3016	●	*	●	●	*	*	●	●	*	*					9.80.2.4		
	AXIS M3024	●	*	●	*	*	*	●	●	*	*							
	AXIS M3024-LVE	●	*	●	*	*	*	●	●	*	*							
	AXIS M3025-VE	●	*	●	*	*	*	●	●	*	*							
	AXIS M3026-VE	●	*	●	*	*	*	●	●	*	*							
	AXIS M3027-PVE (P,C,S)	●	*	●	*	*	*	●	● (TCP)	*	*					5.55.1.2		
	AXIS M3037-PVE (P,C,S)	●	*	●	*	*	*	●	●	●	●		1			*Support motion detection TCP mode after camera FW(8.0.0)		
	AXIS M3044-V	●	*	●	*	*	*	●	●	*	*					6.15.1		
	AXIS M3044-WV	●	*	●	*	*	*	●	●	*	*							
	AXIS M3045-V	●	*	●	*	*	*	●	●	*	*							
	AXIS M3045-WV	●	*	●	*	*	*	●	●	*	*							
	AXIS M3046-V	●	*	●	*	*	*	●	●	*	*							
	AXIS M3047-P (P,C,S)	●	*	●	*	*	*	●	● (TCP)	*	*	*				8.40.3		
	AXIS M3048-P (P,C,S)	●	*	●	*	*	*	●	●	*	●	*	1			*Support motion detection TCP mode after camera FW(8.0.0)		
	AXIS M3057-PLVE (P,C,S)	●	*	●	*	●	●	●	● (TCP)	*	*	*				7.15.2.1		
	AXIS M3058-PLVE (P,S)	●	*	●	*	*	*	●	● (TCP)	*	*	*				7.45.1.1		
	AXIS M3064-V	●	*	●	●	*	*	●	●	*	*	*				9.80.1.2		
	AXIS M3065-V	●	*	●	●	*	*	●	● (TCP)	*	*	*				9.80.2.3		
																9.50.1		
																*Support motion detection TCP mode after camera FW(8.0.0)		

Brand	Camera Model	Compression Format				Zoom Control			Basic Function				Advanced Function				Remark	
		MJPEG	MPEG-4	H.264	H.265	Pan/Tilt	Optical Zoom	Digital Zoom	Motion Detection	Digital Input	Audio (Besides HTTP)	Two-way Audio	Edge Record (RTSP)	Supported IVA	AI Search (Metadata)	Advanced Right-Click Menu	Camera Firmware/ Note	Not support in other platforms CMS, VD, SS
	AXIS M3066-V	●	*	●	●	*	*	●	● (TCP)	*	*	*					9.60.1 *Support motion detection TCP mode after camera FW(8.0.0)	
	AXIS M3067-P (PCCS)	●	*	●	●	*	*	●	● (TCP)	*	*	*					9.80.1 *Support motion detection TCP mode after camera FW(8.0.0)	
	AXIS M3068-P (PCCS)	●	*	●	●	*	*	●	●	*	*	*					9.80.1	
	AXIS M3075-V	●	*	●	●	*	*	●	●	*	●	*	1				10.0.2	
	AXIS M3085-V	●	*	●	●	*	*	●	● (TCP)	*	*	*					10.12.114	
	AXIS M3086-V	●	*	●	●	*	*	●	● (TCP)	*	*	*					11.5.64	
	AXIS M3086-V mic	●	*	●	●	*	*	●	● (TCP)	●X3	●	●	1, 12				11.10.83	
	AXIS M3088-V	●	*	●	●	*	*	●	● (TCP)	*	*	*					10.12.91	
	AXIS M3104-L	●	*	●	*	*	*	●	●	*	*	*						
	AXIS M3104-LVE	●	*	●	*	*	*	●	●	*	*	*					6.15.2	
	AXIS M3105-L	●	*	●	*	●	●	●	●	*	*	*						
	AXIS M3105-LVE	●	*	●	*	●	●	●	●	*	*	*					6.15.2	
	AXIS M3106-L	●	*	●	*	*	*	●	●	*	*	*						
	AXIS M3106-L Mk II	●	*	●	●	*	*	●	●	*	*	*					7.30.1.1	
	AXIS M3106-LVE	●	*	●	*	*	*	●	●	*	*	*						
	AXIS M3106-LVE Mk II	●	*	●	●	*	*	●	●	*	*	*					8.40.1	
	AXIS M3113-R	●	*	●	*	*	*	●	●	*	*	*						
	AXIS M3113-VE	●	*	●	*	*	*	●	●	*	*	*						
	AXIS M3114-R	●	*	●	*	*	*	●	● (TCP)	*	*	*						*Support motion detection TCP mode after camera FW(8.0.0)
	AXIS M3114-VE	●	*	●	*	*	*	●	● (TCP)	*	*	*						*Support motion detection TCP mode after camera FW(8.0.0)
	AXIS M3115-LVE	●	*	●	●	*	*	●	● (TCP)	*	*	*					9.70.1.5 *Support motion detection TCP mode after camera FW(8.0.0)	
	AXIS M3116-LVE	●	*	●	●	*	*	●	●	*	*	*					9.70.1.5	
	AXIS M3203	●	*	●	*	*	*	●	●		●	*	1					
	AXIS M3203-V	●	*	●	*	*	*	●	●		●	*	1					
	AXIS M3204	●	*	●	*	*	*	●	●		●	*	1					
	AXIS M3204-V	●	*	●	*	*	*	●	●		●	*	1					
	AXIS M3205-LVE	●	*	●	●	*	*	●	●	●	*	*					9.50.1	
	AXIS M3077-PLVE (PCCS)	●	*	●	●	*	*	●	●	●	●		1				10.3.3	
	AXIS M3215-LVE	●	*	●	●	*	*	●	● (TCP)	●	●	●	1			Trigger DO X 1	11.8.61	
	AXIS M3216-LVE	●	*	●	●	*	*	●	● (TCP)	●	●	●	1			Trigger DO X 1	11.8.61	
	AXIS M3225	●	*	●	*	*	*	●	● (TCP)	*	*	*	7, 8, 11, 12				9.80.1.2 *Support motion detection TCP mode after camera FW(8.0.0)	
	AXIS M4206-LV	●	*	●	●	*	*	●	●	*	*	*						
	AXIS M4215-LV	●	*	●	●	*	●	●	● (TCP)	*	●	●	1			IR Lamp	11.8.61	
	AXIS M4216-LV	●	*	●	●	*	●	●	● (TCP)	*	●	*	12					
	AXIS M4218-LV	●	*	●	●	*	●	●	● (TCP)	*	●	●	1			IR Lamp	11.8.61	
	AXIS M4317-PLVE (PCCS)	●	*	●	●	*	*	●	● (TCP)	●X1	*	*	12				11.11.73	
	AXIS M4327-P (PCCS)	●	*	●	●	*	*	●	● (TCP)	*	*	*					11.5.64	
	AXIS M4308-PLVE (PCCS)	●	*	●	●	*	*	●	● (TCP)	●	●	●	12				11.5.75	
	AXIS M4328-P (PCCS)	●	*	●	●	*	*	●	● (TCP)	*	*	*					11.5.64	
	AXIS M5013	●	*	●	*	●	●	●	●	*	*	*	1					
	AXIS M5013-V	●	*	●	*	●	●	●	●	*	*	*						

Brand	Camera Model	Compression Format				Zoom Control			Basic Function				Advanced Function				Remark	Not support in other platforms CMS, VD, SS
		MJPEG	MPEG -4	H.264	H.265	Pan/Tilt	Optical Zoom	Digital Zoom	Motion Detection	Digital Input	Audio (Besides HTTP)	Two-way Audio	Edge Record (RTSP)	Supported IVA	AI Search (Metadata)	Advanced Right-Click Menu		
	AXIS M5014	●	*	●	*	●	●	●	●		●	*		1			5.40.11	
	AXIS M5014-V	●	*	●	*	●	●	●	●	*	*	*						
	AXIS M5054	●	*	●	*	●	●	●	●	●	●	*	1			6.53.1.1		
	AXIS M5065	●	*	●	*	●	●	●	●	●	●	*	1			6.53.4.1		
	AXIS M5074	●	*	●	●	●	●	●	(TCP)	*	●	*	1			10.12.91		
	AXIS M5075	●	*	●	●	●	●	●	●	*	●	*	1			10.12.59		
	AXIS M5075-G	●	*	●	●	●	●	●	(TCP)	●	●	*	1			10.12.114		
	AXIS M5525-E	●	*	●	*	●	●	●	●	●	●		1					
	AXIS M5526-E	●	*	●	●	●	●	●	(TCP)	●	●	●	1, 12			11.9.60		
	AXIS P1204	●	*	●	*	*	*	●	●		*	*						
	AXIS P1214	●	*	●	*	*	*	●	●	●	*	*	1					
	AXIS P1214-E	●	*	●	*	*	*	●	●	*	*	*						
	AXIS P1224-E	●	*	●	*	*	*	●	●	*	*	*						
	AXIS P1245	●	*	●	*	*	*	*	●	*	*	*				9.80.2.4		
	AXIS P1265	●	*	●	*	*	*	●	●	*	*	*	7, 8, 11, 12			9.80.2.4		
	AXIS P1275	●	*	●	*	*	*	●	●	*	*	*				9.80.2.4		
	AXIS P1343	●	*	●	*	*	*	●	●	●	*	*	1					
	AXIS P1343-E	●	*	●	*	*	*	●	●	●	*	*	1					
	AXIS P1344	●	*	●	*	*	*	●	●	●	*	*	1					
	AXIS P1344-E	●	*	●	*	*	*	●	●	●	*	*	1					
	AXIS P1346	●	*	●	*	*	*	●	●	●	*	*	1			5.22		
	AXIS P1346-E	●	*	●	*	*	*	●	●	●	*	*	1			5.22		
	AXIS P1347	●	*	●	*	*	*	●	●	●	*	*	1					
	AXIS P1347-E	●	*	●	*	*	*	●	●	●	*	*	1					
	AXIS P1353	●	*	●	*	*	*	●	●	●	*	*	1					
	AXIS P1353-E	●	*	●	*	*	*	●	●	*	*	*	1					
	AXIS P1354	●	*	●	*	*	*	●	●	●	*	*	1			5.60.1.4		
	AXIS P1354-E	●	*	●	*	*	*	●	●	*	*	*	1					
	AXIS P1355	●	*	●	*	*	*	●	●	●	*	*	1					
	AXIS P1355-E	●	*	●	*	*	*	●	●	*	*	*	1					
	AXIS P1357	●	*	●	*	*	*	●	●	*	●	*	1					
	AXIS P1357-E	●	*	●	*	*	*	●	●	*	●	*	1					
	AXIS P1364	●	*	●	*	*	*	●	●	●	*	*						
	AXIS P1364-E	●	*	●	*	*	*	●	●	●	●	*	1					
	AXIS P1365	●	*	●	*	*	*	●	●	●	*	*	1			5.75.3.1		
	AXIS P1365-E	●	*	●	*	*	*	●	●	●	*	*	1			5.75.3.1		
	AXIS P1368-E	●	*	●	*	*	*	●	●	●	*	*	1					
	AXIS P1375	●	*	●	●	*	*	●	●	●	●	●	1			9.50.1		
	AXIS P1375-E	●	*	●	●	*	*	●	●	●	●	●	1			9.80.1.1		
	AXIS P1377	●	*	●	●	*	*	●	●	●	●		2, 4, 6, 7, 8, 11, 12			9.80.2.4		
	AXIS P1378	●	*	●	●	*	*	●	●	*	●	●	1					
	AXIS P1385-E	●	*	●	●	*	*	●	(TCP)	●X2	●	●	1, 12			11.10.55		
	AXIS P1405-LE	●	*	●	*	●	●	●	●	*	*	*				5.55.3.3		
	AXIS P1425-E	●	*	●	*	*	*	●	●	●	*	*	1			5.55.3.3		
	AXIS P1425-LE	●	*	●	*	*	*	●	●	●	*	*	1			5.55.3.3		
	AXIS P1427-E	●	*	●	*	*	*	●	●	●	*	*				5.55.3.3		
	AXIS P1427-LE	●	*	●	*	*	*	●	●	●	*	*	1			5.55.3.3		
	AXIS P1428-E		*	●	*	*	*	●	●	●	*	*				5.55.5.1		
	AXIS P1435-E	●	*	●	*	*	*	●	(TCP)		*	*				*Support motion detection TCP mode after camera FW(8.0.0)		
	AXIS P1435-LE	●	*	●	*	*	*	●	(TCP)		*	*				*Support motion detection TCP mode after camera FW(8.0.0)		
	AXIS P1445-LE	●	*	●	*	*	*	●	●	●	*	*	1			9.30.1 Up to 50/60 fps (50/60 Hz) in HDTV 1080p		
	AXIS P1447-LE	●	*	●	*	*	*	●	●	●	*	*	1			9.80.2.4		
	AXIS P1448-LE	●	*	●	*	*	*	●	●	●	*	*	1			7.35.2.3		

Brand	Camera Model	Compression Format				Zoom Control			Basic Function				Advanced Function				Remark			
		MJPEG	MPEG-4	H.264	H.265	Pan/Tilt	Optical Zoom	Digital Zoom	Motion Detection	Digital Input	Audio (Besides HTTP)	Two-way Audio	Edge Record (RTSP)	Supported IVA	AI Search (Metadata)	Advanced Right-Click Menu	Camera Firmware/ Note	Not support in other platforms CMS, VD, SS		
	AXIS P1455-LE	●	*	●	●	*	●	●	●	●	●	●	●	●	1	●		11.10.56		
	AXIS P1465-LE	●	*	●	●	*	●	●	●	●	●	●	●	1,12						
	AXIS P1467-LE	●	*	●	●	*	●	●	●	●	●	●	1, 12					11.5.64		
	AXIS P1468-LE	●	*	●	●	*	●	●	●	●	●	●	1, 12					10.12.199		
	AXIS P1468-XLE	●	*	●	●	*	●	●	●	●	●	●	1, 12	●X1					11.10.61	
	AXIS P3214-V	●	*	●	*	*	*	●	●	●	●	*	1						5.55.3.3	*Support motion detection TCP mode after camera FW(8.0.0)
	AXIS P3214-VE	●	*	●	*	*	*	●	●	●	●	*	1						5.55.3.3	*Support motion detection TCP mode after camera FW(8.0.0)
	AXIS P3215-V	●	*	●	*	*	*	●	●	●	●	*	1						5.55.3.3	
	AXIS P3215-VE	●	*	●	*	*	*	●	●	●	●	*	1						5.55.3.3	
	AXIS P3224-LV	●	*	●	*	*	*	●	●	●	●	*							6.10.1.1	
	AXIS P3224-LV Mk II	●	*	●	*	*	*	●	●	●	●	*							9.10.1	Up to 50/60 fps (50/60 Hz) in HDTV 720p
	AXIS P3224-V	●	*	●	*	●	●	●	●	●	●	*							6.10.1.1	
	AXIS P3224-VE	●	*	●	*	●	●	●	●	●	●	*							6.10.1.1	
	AXIS P3225-LV	●	*	●	*	●	●	●	●	●	●	*							6.10.1.1	
	AXIS P3225-LVE	●	*	●	*	*	*	●	●	●	●	*							5.75.3	
	AXIS P3225-VE	●	*	●	*	*	*	●	●	●	●	*								
	AXIS P3227-LV	●	*	●	*	*	*	●	●	●	●	*	1						7.15.1.1	
	AXIS P3228-LV	●	*	●	*	*	●	●	●	●	●	*							8.20.1.1	
	AXIS P3228-LVE	●	*	●	*	*	●	●	●	●	●	*							8.20.1.1	
	AXIS P3245-LV	●	*	●	●	*	●	●	●	●	●	●	1						9.40.1.3	*Support motion detection TCP mode after camera FW(8.0.0)
	AXIS P3245-V	●	*	●	●	*	●	●	●	●	●	*							9.60.1	*Support motion detection TCP mode after camera FW(8.0.0)
	AXIS P3247-LVE	●	*	●	●	*	●	●	●	●	●	●	7, 8, 11, 12						10.3.0.3	
	AXIS P3248-LVE	●	*	●	●	*	●	●	●	●	●	●	1						9.80.1.1	
	AXIS P3255-LVE	●	*	●	●	*	●	●	●	●	●	●	1			*			10.4.5	
	AXIS P3265-LV	*	*	●	●	*	*	●	●	●	●	●	1	●		*			10.8.1	
	AXIS P3265-V	●	*	●	●	*	*	●	●	●	●	●	1						10.12.122	
	AXIS P3267-LVE Mic	●	*	●	●	*	●	●	●	●	●	●	1, 12						11.8.61	
	AXIS P3268-LVE	●	*	●	●	*	●	●	●	●	●	●	1, 12						11.6.94	
	AXIS P3301	●	*	●	*	*	*	●	●	●	●	*	1							
	AXIS P3301-V	●	*	●	*	*	*	●	●	●	●	*	1							
	AXIS P3304	●	*	●	*	*	*	●	●	●	●	*	1							
	AXIS P3304-V	●	*	●	*	*	*	●	●	●	●	*	1							
	AXIS P3343	●	*	●	*	*	*	●	●	●	●	*	1							
	AXIS P3343-V	●	*	●	*	*	*	●	●	●	●	*	1							
	AXIS P3343-VE	●	*	●	*	*	*	●	●	●	●	*	1							
	AXIS P3344	●	*	●	*	*	*	●	●	●	●	*	1						5.40.9.5	
	AXIS P3344-V	●	*	●	*	*	*	●	●	●	●	*	1						5.40.9.5	
	AXIS P3344-VE	●	*	●	*	*	*	●	●	●	●	*	1						5.40.9.5	
	AXIS P3346	●	*	●	*	*	*	●	●	●	●	*	1							
	AXIS P3346-V	●	*	●	*	*	*	●	●	●	●	*	1							
	AXIS P3346-VE	●	*	●	*	*	*	●	●	●	●	*	1							
	AXIS P3353	●	*	●	*	*	*	●	●	●	●	*								
	AXIS P3354	●	*	●	*	*	*	●	●	●	●	*								
	AXIS P3363-V	●	*	●	*	*	*	●	●	●	●	*	1							
	AXIS P3363-VE	●	*	●	*	*	*	●	●	●	●	*	1							
	AXIS P3364-L	●	*	●	*	*	*	●	●	●	●	*	1							
	AXIS P3364-LV	●	*	●	*	*	*	●	●	●	●	*								
	AXIS P3364-LVE	●	*	●	*	*	*	●	●	●	●	*								
	AXIS P3364-V	●	*	●	*	*	*	●	●	●	●	*	1							

Brand	Camera Model	Compression Format				Zoom Control			Basic Function					Advanced Function			Remark	Not support in other platforms CMS, VD, SS
		MJPEG	MPEG -4	H.264	H.265	Pan/Tilt	Optical Zoom	Digital Zoom	Motion Detection	Digital Input	Audio (Besides HTTP)	Two-way Audio	Edge Record (RTSP)	Supported IVA	AI Search (Metadata)	Advanced Right-Click Menu		
	AXIS P3364-VE	●	*	●	*	*	*	●	●		●	*		1				
	AXIS P3365-V	●	*	●	*	*	*	●	●		●	*		1			5.55.3.2	
	AXIS P3365-VE	●	*	●	*	*	*	●	●		●	*		1			5.80.1.1	
	AXIS P3367	●	*	●	*	*	*	●	●		●	*		1				
	AXIS P3367-V	●	*	●	*	*	*	●	●		●	*		1				
	AXIS P3367-VE	●	*	●	*	*	*	●	●		●	*		1				
	AXIS P3374-LV	●		●	*	*	*	●	●	●	●	●		1			8.50.1	
	AXIS P3374-V	●		●	*	*	*	●	●	●	●	●		1				
	AXIS P3375-LV	●	*	●	*	*	*	●	●	●	●	●		1			9.80.2.4	
	AXIS P3375-LVE	●	*	●	*	*	*	●	●	●	●	●		1			9.80.2.4	
	AXIS P3375-V	●	*	●	*	*	*	●	●	●	●	●		1			9.80.2.4	
	AXIS P3375-VE	●	*	●	*	*	*	●	●	●	●	●		1			9.80.2.4	
	AXIS P3384-V	●	*	●	*	*	*	●	●		●	*		1				
	AXIS P3384-VE	●	*	●	*	*	*	●	●		●	*		1				
	AXIS P3707-PE	◆	*	●	*	*	*	●	●	*	*	*					5.95.1.1	
	AXIS P3715-PLVE	◆	*	●	*	*	*	●	●	*	*	*					10.1.0	
	AXIS P3717-PLE	◆	*	●	*	*	*	●	●	*	*	*					10.0.2	
	AXIS P3807-PVE	●	*	●	*	*	*	●	●	*	*	*					9.50.1	
	AXIS P3818-PVE	●	*	●	●	*	*	●	(TCP)	●	●	●	●	1			11.8.61	
	AXIS P3905-R	●	*	●	*	*	*	●	●	*	*	*					2.80.1.2	
	AXIS P3905-RE	●	*	●	*	*	*	●	●	*	*	*					2.80.1.2	
	AXIS P3915	●	*	●	*	*	*	●	●		●	*		1			5.55.3	
	AXIS P3915-R Mk II	●	*	●	*	*	*	●	●	●	●	*		1			8.40.2.1	
	AXIS P3925-LRE	●	*	●	●	*	*	●	(TCP)	*	*	*	●				11.5.64	
	AXIS P3925-R	●	*	●	●	*	*	●	(TCP)	*	*	*	●	1			10.12.182	
	AXIS P3935-LR	●	*	●	●	*	*	●	●	●	●	*		1			9.80.1	
	AXIS P5414	●	*	●	*	●	●	●	●	*	*	*						
	AXIS P5414-E	●	*	●	*	●	●	●	●		●	●		1			5.55.1.5	
	AXIS P5415-E	●	*	●	*	●	●	●	●	*	●	●		1				
	AXIS P5512	●	*	●	*	●	●	●	●		*	*						
	AXIS P5512-E	●	*	●	*	●	●	●	●		*	*						
	AXIS P5514	●	*	●	*	●	●	●	●		●	*		1			6.20.1.1	
	AXIS P5514-E	●	*	●	*	●	●	●	●		●	*		1			6.20.1.1	
	AXIS P5515	●	*	●	*	●	●	●	●		●	*		1			5.85.1	
	AXIS P5515-E	●	*	●	*	●	●	●	●		*	*					6.40.1.1	
	AXIS P5522	●	*	●	*	●	●	●	●		●	*		1				
	AXIS P5522-E	●	*	●	*	●	●	●	●		*	*						
	AXIS P5532	●	*	●	*	●	●	●	●		●	*		1				
	AXIS P5532-E	●	*	●	*	●	●	●	●		*	*						
	AXIS P5534	●	*	●	*	●	●	●	●		●	*		1				
	AXIS P5534-E	●	*	●	*	●	●	●	●		*	*						
	AXIS P5544	●	*	●	*	●	●	●	●		*	*						
	AXIS P5624-E	●	*	●	*	*	*	●	●	●	*	*						
	AXIS P5635-E	●	*	●	*	●	●	●	●		●	*		1				
	AXIS P5635-E MKII	●	*	●	*	●	●	●	●		●	*		1			6.35.1	
	AXIS P5654-E	●	*	●	●	●	●	●	●	*	*	*					9.60.1.2	
	AXIS P5654-E Mk II	●	*	●	●	●	●	●	(TCP)	*	*	*	●	12			11.5.64	
	AXIS P5655-E	●	*	●	●	●	●	*	●	●	●	●		1			10.0.0	
	AXIS P5676-LE	●	*	●	●	●	●	●	(TCP)	●	●	●	●	1			11.5.64	
	AXIS P8513	●	*	●	*			●	●			*						
	AXIS P8514	●	*	●	*			●	●			*						
	AXIS Q1602	●	*	●	*	*	*	●	●		●	*		1				
	AXIS Q1602-E	●	*	●	*	*	*	●	●		●	*		1				

Brand	Camera Model	Compression Format				Zoom Control			Basic Function				Advanced Function				Remark	
		MJPEG	MPEG-4	H.264	H.265	Pan/Tilt	Optical Zoom	Digital Zoom	Motion Detection	Digital Input	Audio (Besides HTTP)	Two-way Audio	Edge Record (RTSP)	Supported IVA	AI Search (Metadata)	Advanced Right-Click Menu	Camera Firmware/ Note	Not support in other platforms CMS, VD, SS
	AXIS Q1604	●	*	●	*	*	*	●	●		●	*		1			5.40.3.1	
	AXIS Q1604-E	●	*	●	*	*	*	●	●		●	*		1				
	AXIS Q1614	●	*	●	*	*	*	●	●	*	●	*		1				
	AXIS Q1614-E	●	*	●	*	*	*	●	●	*	●	*		1				
	AXIS Q1615		*	●	*	*	*	●	●		●	*		1			5.80.1.2	
	AXIS Q1615 MKII	●	*	●	*	*	*	●	●	*	●	*		1			7.40.1(Up to 120fps depending on camera resolution)	
	AXIS Q1615-E		*	●	*	*	*	●	●		●	*		1				
	AXIS Q1635	●	*	●	*	*	*	●	●		●	*		1			5.80.1	
	AXIS Q1635-E	●	*	●	*	*	*	●	●		●	*		1			5.80.1	
	AXIS Q1645	●	*	●	*	*	●	●	●	●	●	●		7, 8, 11, 12			9.80.2.4	
	AXIS Q1647	●	*	●	*	*	●	●	●	●	●	●		1			9.80.2.3	
	AXIS Q1656	●	*	●	●	*	●	●	(TCP)	●	●	●	●	1			10.12.182	
	AXIS Q1659	●	*	●	*	●	●	●	●	●	●	●		7, 8, 11, 12			9.80.3.3	
	AXIS Q1755	●	*	●	*	*	*	●	●		●	*		1				
	AXIS Q1755-E	●	*	●	*	*	*	●	●		●	*		1				
	AXIS Q1765-LE	●	*	●	*	●	●	●	●		●	●		1				
	AXIS Q1785-LE	●	*	●	*	*	●	●	●	●	●	*		7, 8, 11, 12			9.80.2.4	
	AXIS Q1808-LE	●	*	●	●	*	●	●	(TCP)	●X2	●	●	●	1, 12			11.8.74	
	AXIS Q1910	●	*	●	*	*	*	●	●		●	*		1				
	AXIS Q1910-E	●	*	●	*	*	*	●	●	*	●	*		1				
	AXIS Q1921	●	*	●	*	*	*	●	●		●	*		1				
	AXIS Q1921-E	●	*	●	*	*	*	●	●		●	*		1				
	AXIS Q1922	●	*	●	*	*	*	●	●		●	*		1				
	AXIS Q1922-E	●	*	●	*	*	*	●	●		●	*		1				
	AXIS Q1931-E	●	*	●	*	*	*	●	●	*	●	*		1				
	AXIS Q1951-E	●	*	●	●	*	*	●	(TCP)	●	●	●		1			11.2.68	
	AXIS Q1961-TE	●	*	●	●	*	*	●	(TCP)	●	●	●	●	1, 4			11.5.75	
	AXIS Q3505	●	*	●	*	*	*	●	●		●	*		1			5.55.3.3	
	AXIS Q3505-V	●	*	●	*	*	*	●	●		●	*		1			5.55.3.3	
	AXIS Q3505-VE	●	*	●	*	*	*	●	●		●	*		1			5.55.3.3	
	AXIS Q3505-VE MKII	●	*	●	*	*	●	●	●		●	*		1			8.10.1	
	AXIS Q3515-LV	●	*	●	*	*	●	●	●	●	●	*		1			50/60fps in HDTV 1080p or 100/120fps in 720p	
	AXIS Q3515-LVE	●	*	●	*	*	●	●	●	●	●	*		1			8.40.1.1	
	AXIS Q3517	●	*	●	*	*	●	●	●	●	●	●		1, 2, 6, 4			9.80.2.4	
	AXIS Q3518-LVE	●	*	●	*	*	●	●	●	●	●	●		7, 8, 11, 12			9.80.2.4	
	AXIS Q3527-LVE	●	*	●	*	*	●	●	●	●	●	●		1, 2, 6, 4			9.80.2.4	
	AXIS Q3536-LVE	●	*	●	●	*	●	●	(TCP)	●	●	●	●	1			10.12.182	
	AXIS Q3615-VE	●	*	●	*	*	*	●	●	*	*	*						
	AXIS Q3617-VE	●	*	●	*	*	*	●	●	*	*	*						
	AXIS Q3709	●	*	●	*	●	●	●	●		●	*		1			5.75.1.1	
	AXIS Q3709-PVE	●	*	●	*	●	●	●	●		●	*		1			5.75.1.1	
	AXIS Q6000	●	*	●	*	●	●	●	*	*	*	*					5.65.1	
	AXIS Q6000 Mk II	●	*	●	*	●	●	●	●	*	*	*						
	AXIS Q6000-E	◆	*	●	*	●	●	●	*	*	*	*					5.65.1	
	AXIS Q6000-E Mk II	◆	*	●	*	●	●	●	●	*	*	*						
	AXIS Q6032	●	*	●	*	●	●	●	●		●	*		1				
	AXIS Q6032-C	●	*	●	*	●	●	●	●	*	*	*						
	AXIS Q6032-E	●	*	●	*	●	●	●	●		*	*						
	AXIS Q6034	●	*	●	*	●	●	●	●		●	*		1				
	AXIS Q6034-C	●	*	●	*	●	●	●	●	*	*	*						
	AXIS Q6034-E	●	*	●	*	●	●	●	●		*	*						
	AXIS Q6035	●	*	●	*	●	●	●	●		●	*		1			5.41.1.1	
	AXIS Q6035-C	●	*	●	*	●	●	●	●	*	*	*						

Brand	Camera Model	Compression Format				Zoom Control			Basic Function				Advanced Function				Remark	
		MJPEG	MPEG-4	H.264	H.265	Pan/Tilt	Optical Zoom	Digital Zoom	Motion Detection	Digital Input	Audio (Besides HTTP)	Two-way Audio	Edge Record (RTSP)	Supported IVA	AI Search (Metadata)	Advanced Right-Click Menu	Camera Firmware/ Note	Not support in other platforms CMS, VD, SS
	AXIS Q6035-E	●	*	●	*	●	●	●	●		●						5.41.1.7	
	AXIS Q6042	●	*	●	*	●	●	●	●	*	*	*						
	AXIS Q6042-C	●	*	●	*	●	●	●	●	*	*	*						
	AXIS Q6042-E	●	*	●	*	●	●	●	●	*	*	*						
	AXIS Q6042-S	●	*	●	*	●	●	●	●	*	*	*						
	AXIS Q6044	●	*	●	*	●	●	●	●	*	*	*						
	AXIS Q6044-C	●	*	●	*	●	●	●	●	*	*	*						
	AXIS Q6044-E	●	*	●	*	●	●	●	●	*	*	*						
	AXIS Q6044-S	●	*	●	*	●	●	●	●	*	*	*						
	AXIS Q6045	●	*	●	*	●	●	●	●	*	*	*						
	AXIS Q6045 Mk II	●	*	●	*	●	●	●	●	*	●	*		1				
	AXIS Q6045-C	●	*	●	*	●	●	●	●	*	*	*						
	AXIS Q6045-E	●	*	●	*	●	●	●	●	*	*	*						
	AXIS Q6045-E Mk II	●	*	●	*	●	●	●	●	*	●	*		1				
	AXIS Q6045-S	●	*	●	*	●	●	●	●	*	*	*						
	AXIS Q6052	●	*	●	*	*	*	●	●	●	*	*						
	AXIS Q6052-E	●	*	●	*	*	*	●	●	●	*	*						
	AXIS Q6054-E	●	*	●	*	*	*	●	●	●	*	*						
	AXIS Q6055	●	*	●	*	●	●	●	●	●	*	*					8.10.1 Up to 50/60 fps (50/60 Hz) in HDTV 720p	
	AXIS Q6055-C	●	*	●	*	●	●	●	●	*	*	*					8.10.1 Up to 50/60 fps (50/60 Hz) in HDTV 720p	
	AXIS Q6055-E	●	*	●	*	●	●	●	●	*	*	*					8.10.1 Up to 50/60 fps (50/60 Hz) in HDTV 720p	
	AXIS Q6055-S	●	*	●	*	●	●	●	●	●	*	*					8.10.1	
	AXIS Q6075-E	●	*	●	*	●	●	●	●	*	*	*					9.40.1.3	
	AXIS Q6114	●	*	●	*	●	●	●	●	*	*	*					5.65.2	
	AXIS Q6114-E	●	*	●	*	*	*	●	●	*	*	*					5.65.2	
	AXIS Q6115-E	●	*	●	*	*	*	●	●	●	*	*						
	AXIS Q6125-LE	●	*	●	●	●	●	●	●	*	*	*				Speed Dry	8.30.1.1 *NVR FW 68 support speed dry	
	AXIS Q6128-E	●	*	●	*	●	●	●	●	*	*	*						
	AXIS Q6135-LE	●	*	●	●	●	●	●	●	*	*	*		2, 6, 4			10.2.0	
	AXIS Q6155-E	●	*	●	*	*	*	●	●	●	*	*						
	AXIS Q6215-LE	●	*	●	*	●	●	●	●	*	*	*				Wiper	9.30.1	
	AXIS Q6225-LE	●	*	●	●	●	●	●	●	(TCP)	*	●	●	1		Wiper, IR Lamp	11.5.70	
	AXIS Q6315-LE	●	*	●	●	●	●	●	●	(TCP)	*	*	●	12			10.12.199	
	AXIS Q8414-LVS	●	*	●	*	*	*	●	●	●	*	*		1				
	AXIS Q8631-E	●	*	●	*	*	*	●	●	●	*	*						
	AXIS Q8632-E	●	*	●	*	●	●	●	●	●	*	*						
	AXIS Q8665-E	●	*	●	*	●	●	●	●	*	*	*						
	AXIS Q8665-LE	●	*	●	*	●	●	●	●	*	*	*					8.10.1	
	AXIS Q8685-LE	●	*	●	*	●	●	●	●	●	*	*				IR, Wiper		
	AXIS Q8721-E	●	*	●	*	*	*	●	●	●	*	*		1				
	AXIS Q8722-E	●	*	●	*	*	*	●	●	●	*	*		1				
	AXIS Q9307-LV	●	*	●	●	●	●	●	●	●	●	●	●	1, 12			11.10.56	
	AXIS T6101	*	*	*	*	*	*	*	*	*	●	●	●	1			*Must be used with AXIS camera	
	AXIS T6101 MK II	*	*	*	*	*	*	*	*	*	●	●	●	1			*Must be used with AXIS camera	
	AXIS V5914	●	*	●	*	●	●	●	●	●	●	*		1			5.75.1	
	AXIS V5915	●	*	●	*	●	●	●	●	●	●	*		1				
	AXIS V5925	●	*	●	●	●	●	●	●	●	●	●		1			10.0.0.1	
AXIS Thermal camera																		
	AXIS P1280-E	●	*	●	*	*	*	●	●	*	*	*		10			9.20.1	
	AXIS P1290-E	●	*	●	*	*	*	●	●	*	*	*		10			9.20.1	
	AXIS Q1932-E	●	*	●	*	*	*	●	●	●	●	*		1, 10			6.50.3	
	AXIS Q1941-E	●	*	●	*	*	*	●	●	●	●	*		1, 10			9.20.1	
	AXIS Q1942-E	●	*	●	*	*	*	●	●	●	●	*		1, 10			6.50.3	
	AXIS Q2901-E	●	*	●	*	*	*	●	●	●	●	*		1, 10				

Brand	Camera Model	Compression Format				Zoom Control			Basic Function				Advanced Function			Remark		
		MJPEG	MPEG-4	H.264	H.265	Pan/Tilt	Optical Zoom	Digital Zoom	Motion Detection	Digital Input	Audio (Besides HTTP)	Two-way Audio	Edge Record (RTSP)	Supported IVA	AI Search (Metadata)	Advanced Right-Click Menu	Camera Firmware/ Note	Not support in other platforms CMS, VD, SS
AXIS Video Server																		
	AXIS F34	●	*	●	*	*	*	●	●		●	*		1			5.85.2	
	AXIS F41	●	*	●	*	*	*	●	●		●	*		1			5.55.3.2	
	AXIS F44	●	*	●	*	*	*	●	●		●	●		1			5.55.3.2	
	AXIS F9111	●	*	●	●	*	*	●	● (TCP)	●	●	●	●	1			11.1.55 *Max 60FPS	
	AXIS F9114	●	*	●	●	*	*	●	● (TCP)	●	●	●	●	1			11.4.63 *Support Qaud Mode *Motion will be triggered in Camera 1 in Qaud Mode *DI is available in Qaud Mode	
	AXIS M7001	●	*	●	*	*	*	●	●		*	*						
	AXIS M7011	●	*	●	*	●	●	●	●	*	*	*					6.50.5.2	
	AXIS M7016	●	*	●	*			●	●		*	*					5.51.1	
	AXIS M7104	●	*	●	●	*	*	●	●	*	●	*		1			9.25.1.5	
	AXIS P7214	●	*	●	*	*	*	●	●		●	●		1				
	AXIS P7304	●	*	●	●	*	*	●	●	*	●	*		1			9.25.1.2	
	AXIS Q7401	●	*	●	*	*	*	●	●		●	*						
	AXIS Q7411	●	*	●	*	*	*	●	●		●	●		1				
	AXIS Q7424-R-MkII	●	*	●	●	*	*	●	●	*	●	*		1, 2, 4, 6, 7, 8, 11, 12			5.51.3.7	
AXIS Video Door Station																		
	AXIS A8105-E	●	*	●	*	*	*	●	●	●	●	●		1			1.65.1.1 *Support Call button event: Digital Input_1(Call button).	
	AXIS I8016-LVE	●	*	●	●	*	*	●	● (TCP)	●	●	●	●	1		Trigger DO x 2	11.7.61 *Support Two-way Talk: Digital Input_1(Call button).	
	AXIS I8116-E	●	*	●	●	*	*	●	● (TCP)	●	●	●	●	1		Trigger DO x 2	11.5.54 *Support Two-way Talk: Digital Input_1(Call button).	
AXIS 295 Video Surveillance Joystick																		
	AXIS 295	*	*	*	*	●	●	*	*	*	*	*						
AXIS T8310 Video Surveillance Control Board																		
	AXIS T8311 Joystick	Please contact DIGIEVER sales.														*Only support remote client		
	AXIS T8312 Keypad	Please contact DIGIEVER sales.														*Only support remote client		
	AXIS T8313 Jog Dial	Please contact DIGIEVER sales.														*Only support remote client		
AXIS I/O BOX																		
	AXIS P8221	*	*	*	*	*	*	*	*	●								
	AXIS D3110	*	*	*	*	*	*	*	*	●							11.1.65 *Support to add as a camera	
AXIS Network Horn Speaker (Click speaker icon on liveview for live speech)																		
	AXIS C3003-E	*	*	*	*	*	*	*	*	●							1.20.0	
	AXIS C1211-E	*	*	*	*	*	*	*	*	●	*	*				Audio Pattern 1~50	10.12.183.1 Note: PC and NVR should be in the same Lan for live speech on liveview	
	AXIS C1310-E	*	*	*	*	*	*	*	*	●	*	*				Audio Pattern 1~50	10.12.183.1 Note: PC and NVR should be in the same Lan for live speech on liveview	

Note:

- More models are under integration and will be released soon.
- Two-way audio: ACTi, AXIS, Brickcom, Canon, Hi-Sharp, Honeywell, Hunt, Levelone, Milesight, Only, ONVIF, Risk Captur, SONY, Sunell, TOA (5-generation camera), VIVOTEK (LAN), WatchNet
- Edge recording: ACTi, AXIS (H.264 only), Airflying, Brickcom, Chiper, Dahua, Dynacolor, Hanwha, Honeywell, HUNT, LILIN, Milesight, Only, Pinetron, SONY(H.264 only), Tecom VIVOTEK, WatchNet
- VB Search supports Canon cameras listed in the compatible list except VB-C series.
- Local liveview supports ImmerVersion engine codec of H.264 and MJPEG only.
- For camera added via ONVIF protocol, please follow below steps to set up camera event (like motion detection, digital input, tampering detection) on DIGIEVER:
 - On DIGIEVER NVR: Enable camera event on event and action management page.
 - On camera webpage: Enable camera event on camera setting page
- NVR supports H.264 and H.265 through ONVIF. For MJPEG format, please use Generic_MJPEG to add the camera.
- NVR supports Honeywell IVA through ONVIF (by Model): Motion Detection, Advanced Motion Detection, Tampering Detection, Intrusion Detection, Loitering Detection, People Counting Threshold Notice
- Cameras are not supported in Camera Digital Output in the Event & Action Management : Canon and TOA

Brand	Camera Model	Compression Format				Zoom Control			Basic Function			Advanced Function				Remark	
		MJPEG	MPEG-4	H.264	H.265	Pan/Tilt	Optical Zoom	Digital Zoom	Motion Detection	Digital Input	Audio (Besides HTTP)	Two-way Audio	Edge Record (RTSP)	Supported IVA	AI Search (Metadata)	Advanced Right-Click Menu	Camera Firmware/ Note

10. "Setting from Camera" supported brand: AXIS(5.00 or below version), Brickcom, Canon, Chiper, Dynacolor, Hunt, iCantek, IDIS, i-Pro (, LILIN, Linksys, MEDIAEDGE, Messoa, Milesight, ONLY, ONVIF, Panasonic (except for BB-HCM, BL, BB-HCE series), PROBE, Provision ISR, Samsung, SECUBEST, Sony, TOA, Topview, VIVOTEK

Note: Settings from camera doesn't support MJPEG for Panasonic cameras. NVR will switch the format to H.265, H.264 or MPEG-4 if users choose MJPEG.

Copyright © DIGIEVER Corporation All Rights Reserved