

DIGIEVER Network Camera Compatibility List

The list is applied for DIGIEVER NVR firmware 78-2 version or later

Update: Oct. 2024

● DIGIEVER NVR supports the camera feature	* Camera does not support the feature	Blank means the feature is NOT supported or verified by DIGIEVER	
Ⓟ 360° Panoramic	Ⓞ NVR support camera hardware dewarp setting	Ⓢ NVR support camera software dewarp	
◆ Camera takes more than 1CH, needed to be added via video sever method			
IVA Event No.:	1. Audio Detection 2. Advanced Motion Detection 3. Human Detection 4. Cross Line Detection	5. Intrusion Detection 6. Loitering Detection 7. Foreign Object Detection 8. Missing Object Detection	9. People Counting Threshold Alarm 10. Temperature Detection 11. Camera Tampering Detection 12. Object Status Change

Supported in the NVR latest version

Copyright © DIGIEVER Corporation All Rights Reserved

* Please contact DIGIEVER sales for updated information

Brand	Camera Model	Compression Format				Zoom Control			Basic Function				Advanced Function			Remark	Not support in other platforms CMS, VD, SS	
		MJPEG	MPEG-4	H.264	H.265	Pan/Tilt	Optical Zoom	Digital Zoom	Motion Detection	Digital Input	Audio (Besides HTTP)	Two-way Audio	Edge Record (RTSP)	Supported IVA	AI Search (Metadata)			Advanced Right-Click Menu
A-MTK	A-MTK cameras																	
	A-MTK AH2030T	●		●	*	*	*	●	●			●						
	A-MTK AH2530T	●		●	*	*	*	●	●			●						
	A-MTK AH2560D	●		●	*	*	*	●	●			●						
	A-MTK AH2560P	●		●	*	*	*	●	●			●						
	A-MTK AH2560T	●		●	*	*	*	●	●			●						
	A-MTK AH2570P	●		●	*	*	*	●	●			●						
	A-MTK AH2570T	●		●	*	*	*	●	●			●						
	A-MTK AH2630P	●		●	*	*	*	●	●			●					6.M.2.9715	
	A-MTK AH2630T	●		●	*	*	*	●	●			●						
	A-MTK AH2706D	●		●	*	*	*	●	●			●						
	A-MTK AH2806T	●		●	*	*	*	●	●			●						
	A-MTK AH2816T	●	*	●	*	*	*	●	●			●						
	A-MTK AH2911D	●		●	*	●	●	●	●	●		●						
	A-MTK AH2930D	●		●	*	*	*	●	●			●						
	A-MTK AM2030D	●		●	*	*	*	●	●			●						
	A-MTK AM2131M	●	*	●	*	*	*	●	●			*						
	A-MTK AM2132M	●	*	●	*	*	*	●	●			*						
	A-MTK AM2180D	●		●	*	*	*	●	●			●						
	A-MTK AM2182D	●		●	*	*	*	●	●			●						
	A-MTK AM2190D	●		●	*	*	*	●	●			●						
	A-MTK AM2192DM	●		●	*	*	*	●	●			●						
	A-MTK AM21C2D	●	*	●	*	*	*	●	●			*						
	A-MTK AM21C3D	●	*	●	*	*	*	●	●			*						
	A-MTK AM2221D	●		●	*	●	*	●	●			●						
	A-MTK AM2231D	●		●	*	●	*	●	●			●						
	A-MTK AM2290D	●		●	*	●	*	●	●			●						
	A-MTK AM2530D	●		●	*	*	*	●	●			●						
	A-MTK AM2560D	●		●	*	*	*	●	●			●						
	A-MTK AM2590D	●		●	*	*	*	●	●			●					6.D.2.9659	
	A-MTK AM2630D	●		●	*	*	*	●	●			●						
	A-MTK AM2703D	●		●	*	*	*	●	●			●						
	A-MTK AM2730D	●		●	*	*	*	●	●			●						
	A-MTK AN2006D	●	*	●	*	*	*	●	●			●						
	A-MTK AN2006D-AEZ4AAO	●	*	●	*	*	*	●	●			●						
	A-MTK AN2563D	●	*	●	*	*	*	●	●			●						
	A-MTK AN2563D-AEZ4AAO	●	*	●	*	*	*	●	●			●						
	A-MTK AN2573D	●	*	●	*	*	*	●	●			●						
	A-MTK AN2606D	●	*	●	*	*	*	●	●			●						
	A-MTK AN2616D	●	*	●	*	*	*	●	●			●						
	A-MTK AN2616D-AEO1BCO	●	*	●	*	*	*	●	●			●						
	A-MTK AN2706D	●	*	●	*	*	*	●	●			●						
	A-MTK AN2706D-AEZ4AAP	●	*	●	*	*	*	●	●			●						

Note:

1. More models are under integration and will be released soon.
2. Two-way audio: ACTI, AXIS, Brickcom, Canon, Hi-Sharp, Honeywell, Hunt, Levelone, Milesight, Only, ONVIF, Risk Captur, SONY, Sunell, TOA (5-generation camera), VIVOTEK (LAN), WatchNet
3. Edge recording: ACTI, AXIS (H.264 only), Airflying, Brickcom, Chiper, Dahua, Dynacolor, Hanwha, Honeywell, HUNT, LILIN, Milesight, Only, Pinetron, SONY(H.264 only), Tecom VIVOTEK, WatchNet
4. VB Search supports Canon cameras listed in the compatible list except VB-C series.

Brand	Camera Model	Compression Format				Zoom Control			Basic Function			Advanced Function			Remark	
		MJPEG	MPEG-4	H.264	H.265	Pan/Tilt	Optical Zoom	Digital Zoom	Motion Detection	Digital Input	Audio (Besides HTTP)	Two-way Audio	Edge Record (RTSP)	Supported IVA	AI Search (Metadata)	Advanced Right-Click Menu

5. Local liveview supports ImmerVersion engine codec of H.264 and MJPEG only.

6. For camera added via ONVIF protocol, please follow below steps to set up camera event (like motion detection, digital input, tampering detection) on DIGIEVER:

(1) On DIGIEVER NVR: Enable camera event on event and action management page.

(2) On camera webpage: Enable camera event on camera setting page

7. NVR supports H.264 and H.265 through ONVIF. For MJPEG format, please use Generic_MJPEG to add the camera.

8. NVR supports Honeywell IVA through ONVIF (by Model): Motion Detection, Advanced Motion Detection, Tampering Detection, Intrusion Detection, Loitering Detection, People Counting Threshold Notice

9. Cameras are not supported in Camera Digital Output in the Event & Action Management : Canon and TOA

10. "Setting from Camera" supported brand: AXIS(5.00 or below version), Brickcom, Canon, Chiper, Dynacolor, Hunt, iCantek, IDIS, i-Pro (, LILIN, Linksys, MEDIAEDGE, Messoa, Milesight, ONLY, ONVIF, Panasonic (except for BB-HCM, BL, BB-HCE series), PROBE, Provision ISR, Samsung, SECUBEST, Sony, TOA, Topview, VIVOTEK

Note: Settings from camera doesn't support MJPEG for Panasonic cameras. NVR will switch the format to H.265, H.264 or MPEG-4 if users choose MJPEG.

Copyright © DIGIEVER Corporation All Rights Reserved